

Workshop

PyPSA-Eur: A Sector-Coupled Open Optimisation Model of the European Energy System

Supported by:



on the basis of a decision by the German Bundestag



Dr. Fabian Neumann Dr. Iegor Riepin

(Technische Universität Berlin)

Dr. Markus Millinger

Gothenburg – 24-25 November 2025

github.com/pypsa/pypsa-eur pypsa-eur.readthedocs.io resilient-project.github.io



What is PyPSA?





Our research focus:

- Cost-effective pathways to reduce greenhouse gas emissions
- Evaluation of grid expansion, hydrogen strategies, carbon management strategies
- Co-optimisation of generation, storage, conversion and transmission infrastructure
- Algorithms to improve the tractability of models
- All open source and open data

Welcome to the PyPSA Community!

PyPSA stands for Python for Power System Analysis.

Free. Open-Source. Batteries included.



GitHub Repository

```
import pypsa

# Create a new network

# Create with a pypsa.Network()

# Add components

n.add("Bus", "mybus")

n.add("Load", "mytoad", bus="mybus", p_set=100)

n.add("Generator", "mygen", bus="mybus", p_nom=100, marginal_cost=20)

# Optimize the network

n.optimize()

# Get statistics

n.statistics.energy_balance()

# Plot results

n.plot()

n.explore()

# Start your journey here ...
```

Application examples












A path out of the gas

PyPSA:Python for Power System Analysis



Capabilities

Capacity expansion (linear)

- single-horizon
- multi-horizon

Market modelling (linear)

- Linear optimal power flow
- N-1 security-constraints
- Unit commitment
- Redispatch
- Rolling-horizon

Non-linear power flow Modelling-to-Generate-Alternatives


With components for

- Electricity transmission networks and pipelines
- Generators with unit commitment constraints
- Variable generation with time series (e.g. wind, solar, hydro)
- Storage with efficiency losses and inflow/spillage for hydro
- Conversion between energy carriers (PtX, CHP, BEV, DAC)


Backend

- all data stored in pandas
- framework built for performance with large networks and time series
- interfaces to major solvers
 (Gurobi, CPLEX, HiGHS, Xpress),
 with linopy (by PyPSA devs)
- highly customisable, but no GUI
- Suitable for greenfield, brownfield & pathway studies





Model short-term market dispatch with unit commitment, renewables, storage, multi-carrier conversion, and more.



Optimize power flow in AC-DC networks using linearized KVL/KCL constraints with optional loss approximations.



Security-Constrained LOPF (SCLOPF)

Ensure system reliability by accounting for line outage contingencies under N-1 conditions.



Capacity Expansion Planning (CEP)

Plan long-term infrastructure investments for generation, storage, transmission, and conversion with continuous or discrete options.



Modular Design

Clean separation between data and modeling code enables flexible scenario development.



Pathway Planning

Co-optimize multi-period investments to design energy transition pathways with perfect foresight planning.



Rolling-Horizon Optimisation

Solve large-scale problems sequentially with myopic foresight and dynamic updates across time horizons.



Stochastic Optimisation

Two-stage stochastic programming for uncertainty handling with weighted scenarios and separate investmentdispatch decisions.



Modelling-to-Generate-Alternatives (MGA)

Explore alternative system designs with similar costs to understand trade-offs and decision flexibility.



Performance

Designed to scale with high-resolution networks, minimizing memory usage and solver overhead.



Policy Constraints

Built-in support for CO2 limits, subsidies, resource limits, expansion limits, and growth constraints.



Custom Constraints

Impose custom objectives, variables and constraints using Linopy for specialized requirements.



Solver Flexibility

Support for wide range of LP, MILP, and QP solvers from open-source to commercial solutions



Data Backbone

Uses pandas for data handling and linopy for optimization with efficient solver interfacing.



Resolution Control

Flexible control over temporal, spatial, and sectoral scope and detail for any analysis needs.



Sector-Coupling

Model integrated multi-carrier energy systems with heat pumps, electrolysers, EVs, and synthetic fuels.



Standard Grid Components

Includes standard types for lines and transformers from pandapower for realistic grid modeling.



Static Power Flow **Analysis**

Compute non-linear and linearised load flows for AC-DC grids using Newton-Raphson method



Visualisations

Plot statistics, time series, spatial distributions of line loadings and dispatch decisions.




Scalability

Handle models from small prototypes to continent-scale systems on highperformance clusters.

PyPSA-Eur: A sector-coupled open model of the European energy system

Automated workflow to build energy system model of Europe from raw open data with high spatial and temporal resolution:

- 1. OSM power lines (>60 kV) + TYNDP
- 2. a database of existing power plants,
- 3. time series for electricity demand,
- 4. time series for wind/solar availability, and
- 5. geographic wind/solar potentials
- 6. cost and efficiency assumptions
- 7. methods for model simplification
- more for sector-coupled networks like pipelines, LNG terminals, electric vehicles, industry locations,



Hydrogen Balance (Hybrid Scenario)

Energy infrastructure planning in PyPSA as an optimisation problem

Find the long-term cost-optimal energy system, including investments and short-term costs:

$$\mathsf{Min}\begin{bmatrix} \mathsf{Yearly} \\ \mathsf{system\ costs} \end{bmatrix} = \mathsf{Min}\begin{bmatrix} \sum_{n} \begin{pmatrix} \mathsf{Annualised} \\ \mathsf{capital\ costs} \end{pmatrix} + \sum_{n,t} \begin{pmatrix} \mathsf{Marginal\ costs} \end{pmatrix} \end{bmatrix}$$


subject to

- meeting energy demand at each node n (e.g. region) and time t (e.g. hour of year)
- transmission constraints between nodes and linearised power flow
- wind, solar, hydro (variable renewables) availability time series $\forall n, t$
- installed capacity < geographical potentials for renewables
- fulfilling CO₂ emission reduction targets
- Flexibility from gas turbines, battery/hydrogen storage, HVDC links





data






Challenges with data-driven modelling

Create a full pipeline of data processing from raw data to results.

- Many different data sources
- Many data sources need cleaning and processing
- Many intermediate scripts and datasets
- Data and software dependencies need to be managed
- Data and code change over time
- Want to be able to reproduce results
- Want to run many different scenarios

Requires a scalable workflow management tool!



snakemake

Originally comes from bioinformatics field.




Miniature example of snakemake

```
Snakefile
   rule mytask:
                                                    rule myplot:
        input:
                                                        input:
            "data/{sample}.txt"
                                                           "result/{sample}.txt"
        output:
                                                        output:
            "result/{sample}.txt"
                                                            "figures/{sample}.pdf"
        script:
                                                        script:
            "scripts/mytask.py"
                                                            "scripts/myplot.py"
```

command: \$ snakemake figures/myfigure.pdf






Simplified workflow structure


Automated **downloads**

Process the data **Build** the electricity system model **Extend** the model by other sectors (later) Solve, summarize & visualize the results


First, raw data is automatically downloaded.
















eurostat •

Simplified workflow structure

Automated downloads

Process the data

Build the electricity system model

Extend the model by other sectors

(later)


Solve, summarize & visualize the results

Steps to building PyPSA-Eur electricity system

Retrieve onshore & offshore polygons for each country

build_shapes

Country shapes & exclusive economic zones (EEZ)



NUTS administrative regions (NUTS3)



Steps to building PyPSA-Eur electricity system

Retrieve onshore & offshore polygons for each country

Construct a base medium- to high-voltage network with buses, transformers, AC & DC lines with DLR & TYNDP

build_shapes

base_network,
build_transmission_projects

Power grid topology

OpenStreetMap data



Apply **standard line types** for capacity and parameters.

Calculate **dynamic line rating** potential from weather data.


TYNDP projects



European network with

- ~5,800 buses
- ~7,300 AC lines (>220 kV)
- 36 HVDC links (+TYNDP)
- Optionally down to 60 kV

https://www.nature.com/articles/s41597-025-04550-7



Steps to building PyPSA-Eur electricity system

Retrieve onshore & offshore polygons for each country

Construct a base high-voltage network with buses, transformers, AC & DC lines with DLR & TYNDP

Transform all transmission lines to 380 kV, remove dead ends & cluster with k-means or hierarchical clustering

build_shapes

base_network,
build_transmission_projects


simplify_network,
cluster_network

Clustering the electricity network: simplify_network _____

Need to make the optimization problem less **computationally challenging**...

...if we want to **co-optimise** generation, storage, PtX conversion and transmission infrastructure:


- Lift all lines to common voltage level of 380 kV.
- Remove dead ends.




cluster_network

Transformed to 380 kV

Clustered to **512 regions**







cluster_network

Transformed to 380 kV

Clustered to **256 regions**







cluster_network

Transformed to 380 kV

Clustered to **128 regions**







cluster_network

Transformed to 380 kV

Clustered to **64 regions**







cluster_network

Transformed to 380 kV

Clustered to **41 regions**





Steps to building PyPSA-Eur electricity system

Retrieve onshore & offshore polygons for each country	build_shapes
Construct a base high-voltage network with buses, transformers, AC & DC lines with DLR & TYNDP	<pre>base_network, build_transmission_projects</pre>
Transform all transmission lines to 380kV, remove dead ends & cluster with k-means or hierarchical clustering	simplify_network, cluster_network
Determine eligible areas for utility-scale PV & onshore/offshore wind park development	<pre>determine_availability_matrix</pre>
Build renewable capacity factor profiles for each clustered region based on land availability	<pre>build_renewable profiles, build_hydro_profile</pre>

atlite: Convert weather data to energy systems data

pypi v0.4.1 conda-forge v0.4.1 Tests passing codecov 72% docs passing license MIT REUSE compliant


JOSS 10.21105/joss.03294 chat 63 online stackoverflow pypsa questions 38


Python library for converting **weather data** (e.g. wind, solar radiation, temperature, precipitation) into **energy systems data**:


- solar photovoltaics
- solar thermal collectors
- wind turbines
- hydro run-off, reservoir, dams
- heat pump COPs
- dynamic line rating (DLR)
- heating and cooling demand (HDD/CDD)


It can also perform **land eligibility analyses**.

Rule: build_renewable profiles










Time series for renewables

Historical meteorological weather data from ERA5 and SARAH-3 (up to 84 years, 30x30 km)

-600 ~

200

tre or



attr: influx direct - time: 2013-03-01T00:00:00

Solar panel models


- orientation
- material


Wind turbine models


- power curve
- surface roughness

atlite: Convert weather data to energy systems data











Land availability for renewables







atlite: Convert weather data to energy systems data



- CORINE / LUISA land cover
 - eligible land types
 - distance requirements
- NATURA / WDPA natural protection areas
- GEBCO bathymetry data
- Shipping lanes
- Distance to shore

Steps to building PyPSA-Eur electricity system

Retrieve onshore & offshore polygons for each country	build_shapes
Construct a base high-voltage network with buses, transformers, AC & DC lines with DLR & TYNDP	<pre>base_network, build_transmission_projects</pre>
Transform all transmission lines to 380kV, remove dead ends & cluster with k-means or hierarchical clustering	simplify_network, cluster_network
Determine eligible areas for utility-scale PV & onshore/offshore wind park development	determine_availability_matrix
Build renewable capacity factor profiles for each clustered region based on land availability	<pre>build_renewable profiles, build_hydro_profile</pre>
Prepare existing renewables and fossil power plants	build_powerplants

Welcome to powerplantmatching's documentation!



A toolset for cleaning, standardizing and combining multiple power plant databases.


import powerplantmatching as pm df = pm.powerplants(from url=True) df.query("DateIn > 2000")

Sources

- Global Energy Monitor (GEM)
- Open Power System Data (OPSD)
- Global Energy Observatory
- World Resources Institute
- Marktstammdatenregister (MaStR)
- CARMA
- ENTSO-E, BNetzA, UBA, IRENA
- JRC for hydro power plants
- European Energy Storage Inventory

Attributes

- name / block
- fuel type
- technology
- country
- capacity
- commissioning year
- retirement year
- coordinates




Steps to building PyPSA-Eur electricity system

Retrieve onshore & offshore polygons for each country	build_shapes
Construct a base high-voltage network with buses, transformers, AC & DC lines with DLR & TYNDP	<pre>base_network, build_transmission_projects</pre>
Transform all transmission lines to 380kV, remove dead ends & cluster with k-means or hierarchical clustering	<pre>simplify_network, cluster_network</pre>
Determine eligible areas for utility-scale PV & onshore/offshore wind park development	determine_availability_matrix
Build renewable capacity factor profiles for each clustered region based on land availability	<pre>build_renewable profiles, build_hydro_profile</pre>
Prepare existing renewables and fossil power plants	build_powerplants
Add generation, storage and demand to the network with techno-economic assumptions on costs and efficiencies,	add_electricity, prepare_network

Open database of techno-economic assumptions

- compiles techno-economic assumptions on energy system components
 - investment costs, FOM/VOM costs, efficiencies, lifetimes
 - o for given years, e.g. 2020, 2030, 2040, 2050
 - o from mixed sources, but prioritising **Danish Energy Agency** where available (and sensible)



Options for temporal aggregation


Multiple options:

- 1. **averaging** of every Nth hour
- 2. **sampling** every Nth hour (e.g. 3-hourly)
- 3. Non-equidistant **segmentation** with pre-defined number of segments using the **tsam** Python library from **FZ Jülich**

Introduction



tsam - time series aggregation module



Simplified workflow structure

Automated downloads

Process the data

Build the electricity system model

Extend the model by other sectors

(later)

Solve, summarize & visualize the results

linopy: Linear optimization with N-D labeled variables








It supports:

- Linear (LP),
- Mixed-Integer (MILP),
- Quadratic programming (QP).

It has been developed to make linear programming in Python easy, highly-flexible and – most importantly – highly performant.




Solving and summarising networks

Hardware requirements:

- Building the model can run locally on most modern laptops. Very simple models can run with HiGHS solver.
- But access to a commercial solver and a larger cluster/workstation is required for solving problems (~250 GB RAM per scenario if resolution is very high)!


There is a **statistics module in PyPSA** designed to help with analysing solved networks and several **figures/maps are created automatically**.




What is configurable?

electricity-only examples

- Select subset of countries and focus countries (e.g. only DE)
- Select weather year (1940 2024 for ERA5)
- Specify CO₂ constraint and gas usage limit
- Tweak spatial resolution (between 41 and >1000 nodes)
- Tweak temporal resolution (from hourly to N-hourly)
- Customize cost assumptions (e.g. 2020, 2030, 2050)
- Parametrize technologies (e.g. wind turbine type, panel orientation)
- Define land use eligibility criteria (e.g. distance requirements)
- Pick a solver (HiGHS, Gurobi, CPLEX, Xpress...)
- Choose between greenfield or brownfield expansion





Ctrl + K



Introduction

Installation

Tutorial: Electricity-Only

Tutorial: Sector-Coupled

Configuration

Wildcards

Configuration

Foresight Options

Techno-Economic Assumptions

Rules Overview

Retrieving Data

Building Electricity Networks



https://pypsa-eur.readthedocs.io /en/latest/configuration.html

Configuration

PyPSA-Eur has several configuration options which are documented in this section.

Configuration Files

Any PyPSA-Eur configuration can be set in a <code>.yaml</code> file. The default configurations <code>config/config.default.yaml</code> and <code>config/plotting.default.yaml</code> are maintained in the repository and cover all the options that are used/ can be set.

To pass your own configuration, you can create a new file, e.g. my_config.yaml, and specify the options you want to change. They will override the default settings and options which are not set, will be inherited from the defaults above.

Another way is to use the <code>config.yaml</code> file, which does not exist in the repository and is also not tracked by git. But snakemake will always use this file if it exists. This way you can run snakemake with a custom config without having to specify the config file each time.

Configuration order of precedence is as follows: 1. Command line options specified with --config (optional) 2. Custom configuration file specified with --configfile (optional) 3. The config/config.yaml file (optional) 4. The default configuration files config/config.default.yaml and config/plotting.default.yaml

To use your custom configuration file, you need to pass it to the snakemake command using the --configfile option:

\$ snakemake -call --configfile my_config.yaml



Configuration Files

Top-level configuration

run

foresight

scenario

countries

snapshots

enable

co2 budget

electricity

atlite

renewable

conventional

lines

links

transmission projects

transformers

load

energy

biomass

solar_thermal

existing_capacities

sector

industry

costs

clustering



Live Demo – Belgium / electricity-only / few days

Start with a dry-run:

Don't forget to activate your conda environment first!

\$ snakemake -c1 solve_elec_networks --configfile config/test/config.electricity.yaml -n

Then execute the same command "for real" by dropping "-n" flag:

The "-c1" flag tells snakemake to run one job at a time; "-call" to use all cores.

\$ snakemake -call solve_elec_networks --configfile config/test/config.electricity.yaml

To explore results, start a Jupyter notebook:

\$ jupyter notebook

Practical Phase

(electricity-only)

2) Install conda environment

Installation links:

- Anaconda (bigger download):
- Miniconda (recommended):
- \$ conda update conda
- \$ conda env create -f envs/environment.yaml
- \$ conda activate pypsa-eur
- **4)** Explore PyPSA network in a Jupyter notebook

```
import pypsa
fn = "results/test-elec/networks/base_s_5_elec_.nc"
n = pypsa.Network(fn)
n.statistics()
n.plot()
```

1) Download the repository

Open a terminal / CMD / Anaconda Prompt and type:

- \$ cd ~/path/to/my/directory
- \$ git clone https://github.com/PyPSA/pypsa-eur.git
- \$ cd pypsa-eur





3) Run PyPSA-Eur tutorial with snakemake

Guide:

https://pypsa-eur.readthedocs.io/en/latest/tutorial.html

\$ snakemake -call solve_elec_networks
--configfile
config/test/config.electricity.yaml

Users of Windows, add two lines to YAML:
run:
use_shadow_directory: false

Small exploratory configuration tasks

(electricity-only)

Go to https://pypsa-eur.readthedocs.io/en/latest/configuration.html and https://github.com/PyPSA/pypsa-eur/blob/master/config/config.default.yaml and try to find out how to configure some of the settings for **electricity-only models** listed below:

- 1. Increase the maximum line loading from 70% to 100%.
- 2. Disable power transmission grid reinforcements.
- 3. Activate dynamic line rating with default settings.
- 4. Activate linearised transmission loss approximation.
- 5. Deactivate the estimation of existing renewable capacities.
- 6. Change the techno-economic assumptions to the year 2020.
- 7. Remove the option to build hydrogen or battery storage.

Simplified workflow structure

Automated downloads

Process the data


Build the electricity system model


Extend the model by other sectors

Solve, summarize & visualize the results

Coupling with other sectors


- transport sector (EVs, shipping, aviation)
- heating sector (district heating, individual)
- industry sector (steel, chemicals, ammonia, ...)
- carbon management (CCUTS) + biomass
- hydrogen, CO₂ and gas networks








Extension by other sectors requires more data!






Spatial distribution of energy demands




Use of PyPSA components

- **Buses** impose energy balances for different energy carriers (heat, hydrogen, methane), and account for CO₂ emitted/absorbed from the atmosphere.
- **Links** represent **energy converters**, e.g. a heat pump that withdraws energy from the electricity bus and supplies heat to the heating bus with a certain efficiency.
- ullet Multilinks represent more elaborated conversion processes, e.g. a biomass-fired CHP that withdraws biomass and supplies electricity, heat and ${\rm CO_2}$ emissions.
- **Stores** can represent available potential (if allowed to discharge throughout the modelled period) or relax the hourly energy balancing constraint to annual (when a free store is added).

Transport - Electrification of land transport






- Road and rail are largely electrified, ICE
 only during pathway to net-zero
- Time series from traffic counting
- Lumped representation of electric
 vehicles: a configurable share of them
 participates in demand-side management
 (DSM) or vehicle-to-grid (V2G)
- Electric vehicles have time-varying
 availability for charging depending on driving profiles
- EV battery almost fully charged in the

Modelling **land transport transformation** endogenously is currently under development!



Heating - Demand



Heating demand time series created by :

- space heating based on degree-day and daily profiles, weighted by population
- constant water heating demand
- scaled to historical annual demand
- split into individual and central systems (cooling demand already electrified)

Heating - Tech for individual & district heating

Decentral individual heating

can be supplied by:

- air- or ground-sourced heat pumps
- resistive heaters
- gas / oil / biomass / hydrogen boilers
- solar thermal
- small water tanks


Building renovations can be co-optimised to reduce space heating demand.

District heating systems


can be supplied in urban areas by:

- air-sourced heat pumps + other
- resistive heaters
- gas / hydrogen / biomass / waste CHPs
- gas / oil / biomass / hydrogen boilers
- solar thermal
- long-duration hot water storage
- waste heat from industrial processes






Heating - Heat pumps as new variable supply tech



Geothermal heat sources have been integrated very recently!



Heating - Example daily heat system balance



There are difficult periods in winter with low wind and solar, high space heating demand and low air temperatures, which are bad for air-sourced heat pump performance. In this case gas boilers and CHP plants jump in as backup.

Synthetic fuels - Power-to-X

Carbonaceous fuels produced synthetically:

Synthetic methane using Sabatier reaction

$$CO_2 + 4H_2 \rightarrow CH_4 + 2H_2O$$


Synthetic oil via Fischer-Tropsch

$$(2n+1) H_2 + n CO \rightarrow C_n H_{2n+2} + n H_2 O$$

Synthetic methanol in methanolisation plants

$$CO_2 + 3H_2 \rightarrow CH_3OH + H_2O$$

Industry - Regionalisation based on Hotmaps



Iron & Steel	Phase-out integrated steelworks; increased recycling; rest from H ₂ -DRI + EAF
Aluminium	Methane for high-enthalpy heat; increased recycling
Cement	Solid biomass; capture of CO ₂ emissions
Ceramics	Electrification
Ammonia	Gray, blue, green hydrogen
Plastics	Synthetic naphtha; MtO/MtA, increased recycling
Other industry	Electrification; process heat from biomass
Shipping	Methanol, (oil), (liquid hydrogen), (LNG)
Aviation	Kerosene from Fischer-Tropsch or methanol

Modelling **industry relocation, high-temperature heat source & shipping fuels** endogenously is currently under development!

Infrastructure - Gas network with H₂ retrofitting


Compiled from open **SciGRID_gas** dataset.

Fossil gas enters at **LNG terminals** or **gas fields**.


Gas flow **physics** and **valve control** neglected transport model.

Electricity demand for **compression** and **leakage** configurable.

Pipelines can be **retrofitted** to H_2 with costs from EHB.



Infrastructure - Hydrogen storage potentials



The regional distribution of **geological potential** to store hydrogen in **salt caverns** is considered.


The user can **configure** if onshore and/or offshore potentials can be used.

Dilara Gulcin Caglayan, Nikolaus Weber, Heidi U. Heinrichs, Jochen Linßen, Martin Robinius, Peter A. Kukla, Detlef Stolten, *Technical potential of salt caverns for hydrogen storage in Europe*, **International Journal of Hydrogen Energy**, Volume 45, Issue 11, 2020, 6703, 6805

Volume 45, Issue 11, 2020, 6793-6805, https://doi.org/10.1016/j.ijhydene.2019.12.161



Infrastructure - Biomass from JRC ENSPRESO




Biomass potentials are split between **solid biomass** and **biogas** (which can be, for instance, upgraded).

The user can configure <u>low/medium/high</u> potentials and what <u>categories</u> of biomass to consider (e.g. forest residues).

The default configuration only considers **residual biomass**, no energy crops.

Infrastructure - Carbon management



Built-in carbon flows:


- Capture:

 DAC, process
 emissions, fossil /
 biomass CHP
- **Transport:** CO₂ pipelines
- Storage: intermediate storage and long-term geological sequestration
- Utilization: for synthetic carbonaceous fuels



Infrastructure - Carbon sequestration potentials

Example: Offshore carbon sequestration potentials



The user can configure

- onshore/offshore sequestration,
- gas fields/oil fields/aquifer, and
- low/medium/high potentials,

as well as a **total limit** on the annual sequestration, e.g. 250 Mt per year.

Data source:



https://energy.ec.eur opa.eu/publications/a ssessment-co2-stora ge-potential-europe-c o2stop_en

Technology choices - endogenous vs. exogenous

Exogenous assumptions (modeller chooses):


- energy services demand (e.g. heat)
- district heating shares
- energy carrier shares for road transport
- kerosene for aviation
- methanol for shipping
- electrification & recycling in industry
- steel production with DRI + EAF


Endogenous choices (model optimizes):


- change in electricity generation fleet
- transmission reinforcement
- capacities and locations of short and long-duration energy storage
- space and water heating technologies (including building renovations)
- all P2G/L/H/C
- supply of process heat for industry
- carbon capture (e.g. CHP, industry, DAC)




Prices in the model










Prices in the model

Pumped Hydro Storage

Reservoir & Dam

Run Of River



Supply, consumption and storage options by carrier

Withdrawal

Electricity (115 regions)

Supply

rooftop solar utility-scale solar onshore wind offshore wind (fixed-pole/floating, AC/DCconnected) nuclear hydro reservoirs pumped-hydro run-of-river

run-of-river
import by HVDC link
gas CHP (w/wo CC)
biomass CHP (w/wo CC)
gas turbine (OCGT)
methanol turbine (OCGT)
hydrogen turbine (OCGT)
hydrogen fuel cell CHP
battery discharger
vehicle-to-grid

Withdrawal

industry electricity residential electricity services electricity agriculture electricity air-sourced heat pump ground-sourced heat pump resistive heater electric vehicle charger battery charger pumped-hydro hydrogen pipeline (compression) direct air capture Haber-Bosch electric arc furnace direct iron reduction distribution arid losses transmission grid losses methanolisation electrolysis

Grids & Storage

distribution grid transmission grid battery storage pumped-hydro storage electric vehicles

Hydrogen (115 regions)

import by pipeline import by ship electrolysis chlor-alkali electrolysis (exogenous) steam methane reforming

Supply

(w/wo CC)
ammonia cracker

Fischer-Tropsch methanolisation electrobiofuels direct iron reduction Haber-Bosch hydrogen turbine (OCGT) hydrogen fuel cell CHP methanol-to-kerosene Sabatier

Grids & Storage new pipelines retrofitted pipelines storage in salt caverns storage in steel tanks

Methane (not spatially resolved)

Supply	Withdrawal
import by ship fossil gas biogas upgrading (w/wo CC) Sabatier	gas for high-T industry heat (w/wo CC) steam methane reforming (w/wo CC) gas boiler (rural/urban) gas CHP gas turbine (OCGT)
Storage hydrocarb	oon storage

Liquid Hydrocarbons (not spatially resolved)

Supply
import by ship
fossil oil refining
Fischer-Tropsch
electrobiofuels

Withdrawal
kerosene for aviation
naphtha for industry
diesel for agriculture

Methanol (not spatially resolved)

Supply	Withdrawal
import by ship methanolisation	methanol turbine (OCGT) methanol for shipping methanol for industry methanol-to-kerosene
Storage	hydrocarbon storage

Ammonia (not spatially resolved)

Supply		Withdrawal
import by ship		ammonia cracker
Haber-Bosch		ammonia for fertilizer
Storage	ammonia	a tank

Supply, consumption and storage options by carrier

Heat (115 regions)

Supply Withdrawal air-sourced heat pump residential heat ground-sourced heat pump (only services heat rural) agriculture heat resistive heater low-T industry heat gas boiler direct air capture biomass boiler water tank charger solar thermal water tank discharger biomass CHP (w/wo CC, only DH) gas CHP (w/wo CC, only DH) hydrogen fuel cell CHP (only DH) electrolysis (only DH) Haber-Bosch (only DH) Sabatier (only DH) Fischer-Tropsch (only DH) methanolisation (only DH)

long-duration thermal storage (only DH) Storage hot water tank


CO2 atmosphere (not spatially resolved)

Supply	Withdrawal
kerosene for aviation diesel for agriculture methanol for shipping methanol for industry naphtha for industry gas boiler gas CHP (w/wo CC) gas turbine (OCGT) methanol turbine (OCGT) process emissions (w/wo CC) fossil oil refining gas for high-T industry heat (w/wo CC) steam methane reforming (w/wo CC)	solid biomass for industry (w CC) solid biomass CHP (w CC) biogas upgrading (w CC) direct air capture electrobiofuels

CO2 commodity (not spatially resolved)

coz commounty (not spatially resolved)			
Supply		Withdrawal	
direct air capture biogas upgrading (w CC) gas CHP (w CC) biomass CHP (w CC) steam methane reforming (w CC) process emissions (w CC) solid biomass for industry (w CC) gas for high-T industry heat (w CC)		Fischer-Tropsch methanolisation sequestration Sabatier	
Storage	intermediate storage in steel tank long-term geological sequestration		

PyPSA-Eur can be run on different weather years!




The years **2010**, **2013**, **2019** and **2023** are currently available "out of the box".

Other years 1940-2024 require a few more steps.

We are planning to expand the number of "plug-and-play" years.


Overnight and pathway optimisation

- **Overnight** optimisation builds the complete system in one go. Already existing capacities can be included (**brownfield**) or the system can be built from scratch (**greenfield**)
- The choice of **investment years** is arbitrary.
- Pathway optimisation with myopic foresight (next slide). The CO₂ emission reduction path is exogenous.
- Perfect foresight pathway planning is currently experimental (i.e. use the CO₂ budget endogenously).



Myopic pathway optimization

- The CO₂ emission **reduction path** is exogenous.
- Optimise start network for e.g. 2025, starting with existing energy infrastructure.
- Take results from 2025 as input for 2030 infrastructure optimisation, take 2030 results for next iteration, etc.
- Infrastructure decommissioned when reaching end of lifetime
- Configurable social discount rate and number of planning horizons



Scenario management

PyPSA-Eur has integrated & scalable scenario management.

config/config.yaml

```
run:
  name: all
  scenarios:
    enable: true
scenario:
  clusters: [90]
sector:
 H2 network: true
  gas network: true
 H2 retrofit: true
electricity:
  transmission limit: vopt
```

```
With these two files configured, run:

$ snakemake all -n

and

$ snakemake all
```

config/scenarios.yaml

```
no-h2-network:
  sector:
    H2 network: false
no-grid-expansion:
  electricity:
    transmission limit: v1.0
no-to-both:
  sector:
    H2 network: false
  electricity:
    transmission limit: v1.0
ves-to-both:
  sector:
    H2 network: true
  electricity:
    transmission limit: vopt
```

Live Demo – very similar to electricity-only case

```
Start with a dry-run:
```

```
$ snakemake -call --configfile config/test/config.overnight.yaml -n
```

Then execute the same command "for real" by dropping "-n" flag:

```
$ snakemake -call all --configfile config/test/config.overnight.yaml
```

And for myopic pathway optimisation:

```
$ snakemake -call all --configfile config/test/config.myopic.yaml
```

To explore results, start a Jupyter notebook:

```
$ jupyter notebook
```

Practical Phase

(sector-coupled)

1) Run PyPSA-Eur sector-coupling tutorial with snakemake

Guide:

https://pypsa-eur.readthedocs.io/en/latest/tutorial_sector.html

snakemake -call all --configfile config/test/config.overnight.yaml

2) Explore CSV files and images in results directory.

Go to https://pypsa-eur.readthedocs.io/en/latest/configuration.html and try to find out how to configure some of the settings for **sector-coupled models** listed below:

- 1. Disable vehicle-to-grid discharging.
- 2. Disable hydrogen network expansion.
- 3. Increase the carbon sequestration potential to 800 Mt/a.
- 4. Allow hydrogen underground storage also onshore.
- 5. Reduce the primary production of plastics by increasing recycling rates.